

# StarterAdapter™ SMA

ADAPTER WITH TWO RP-SMA FEMALE CONNECTORS

The StarterAdapter™ SMA converts waveguide interface into coaxial RP-SMA for Horizontal and Vertical polarization. Adapter enables using radios with coaxial interface with any StarterDish™ antennas.



## TECHNICAL DATA

Antenna Connection	Waveguide Port
Radio Connection	2x RP-SMA female
Materials	Insert - Aluminium Alloy Adapter - UV stabilized and weather resistant ABS plastic
Flame Rating	UL 94 HB
Temperature	-40°C to +60°C (-40°F to +140°F)
Wind Survival	160 km/h (100 mi/h)
Weight	0.12 kg (0.26 lbs) – single unit* 0.16 kg (0.35 lbs) – single unit incl. package* 17.0 kg (37.4 lbs) – carton (100 units)
Single Unit	Retail Box: 120 × 75 × 75 mm (4.7 × 2.9 × 2.9 inch)
100 Units	Carton Box: 780 × 410 × 260 mm (30.7 × 16.1 × 10.2 inch)

## PERFORMANCE

Frequency Range	5150 - 5950 MHz
Polarization	Dual Linear H + V
VSWR Max	1.8
Impedance	50 Ohm

## COMPATIBLE WIRELESS PLATFORMS

RF elements® any StarterDish™ Antennas

## PRODUCT DIMENSIONS

